

Programming Flexible Buttons on the SBX-IP 320

1. Press TRANS/PGM
2. Press the flexible button to be programmed.
3. Enter the applicable feature code from the following table.
4. Press HOLD/SAVE to save the setting.

Function	Code	Function	Code
Account Code	PGM + 80	Record User Greeting	PGM + 61
Alarm Reset	565	Register Station Name	PGM + 74
Auth. Code Change	PGM + 32	Record User Greeting	PGM + 61
Auth. Code Register	PGM + 31	Register Station Name	PGM + 74
Background Music	PGM + 73	REDIAL Button	TRANS + 97
Call Log	PGM + 57	Ring Answer Mode	PGM + 12
Call Park	601 - 608	Ring Type	PGM + 11
Camp-On	PGM + 85	Set Customer MSG	PGM + 52
COS Down	PGM + 21	Set Pre-Selected MSG	PGM + 51
COS Restore	PGM + 22	Set Wake-Up Time	PGM + 41
Direct Station Select	100 - 131	Speaker/Headset	PGM + 75
Erase Page MSG	PGM + 67	Two-Way Recording	PGM + 54
Erase User Greeting	PGM + 66	Universal Night Answer	569
Group Call Pick Up	PGM + 71	Wake-Up Disable	PGM + 42
H - T - P	PGM + 12	Walking COS	PGM + 23
Headset Ring Mode	PGM + 76		
Hunt Group	620 - 629	Outside Line Access	
ICM Hold	PGM + 83	Group	801 - 808
LCD Display Language	PGM + 71	Group Access	9
Listen Station Number	PGM + 63	Individual Line Access	8801 - 8812
Listen Station Status	PGM + 64		
Listen Time & Date	PGM + 62	Speed Dial	
LOOP Button	PGM + 84	Station Speed Dial	SPEED + 000-099
MPB Version Display	PGM + 72	System Speed Dial	SPEED + 2000-2449
Record Page MSG	PGM + 65	Ring Answer Mode	PGM + 12